

H 1 4 R multi-point rod kit for hinged security doors ILLUSTRATED FITTING INSTRUCTIONS

1.

Prepare Door

Prepare the door according to the table and diagram below, to suit the application.

	Code	[A]	[B]
High	H14R/H	682 mm	826 mm
Low	H14R/L	826 mm	682 mm
Suit 1500	H14R/P	375 mm	961 mm
Sample	H14R/S	375 mm	348 mm





Follow this step if using Adjustable Rods, otherwise go to Step 3.

Mark the cutout dimensions **A** and **B** on the *Measurement Guide* provided. <u>NOTE</u>: The standard cutout dimensions are pre-marked.

If you are fitting several doors with the same cutout dimensions, it is recommended that you securely tape the *Measurement Guide* to a solid benchtop or hard surface. Then drill holes (4.5mm diameter) to locate and secure the rod ends while fastening.



Adjust the *steel rods* outward until they align with the correct marks on the Measurement Guide. The *coupling* should be spaced in the center between the two *rod ends*, and have the larger *central hole* facing upwards.

NOTE: If the distance between the straight rod end and the bent rod end marked "REMOTE LOCK" (with tape) is less than 50mm (as shown above), you must cut-down the rods enough to provide this clearance. The minimum clearance at the other end is 100mm.

The *rod ends* must be pointing <u>downwards</u> into the benchtop. If you are not drilling holes for the *rod ends*, you will need to place a hard and flat block (10mm thick) under the *coupling*.



CHECK THAT THE ROD ENDS ARE PARALLEL AND POINTING STRAIGHT DOWN. Re-align if necessary and check the overall length.

Insert the pointed end of the *drive pin* into the *rolled steel pin* (already pressed into the into the large *central hole*) and hammer until it is fully inside the *coupling*.



Install Remote Locks

Rod lengths for each application are given in the table below for reference.

3

Fit a supplied *o-ring* on each rod 60 - 80mm from the remote end (not needed for Adjustable Rods).

Assemble corresponding *rods* to the *top* and *bottom remote locks*, ensuring the *UP arrows* on the *remote locks* are pointing towards the top of the door.

With the *top remote lock* connected to the *top rod*, slide the *free-end* of the *top rod* though the *top remote lock cutout*.

Repeat the above process for the *bottom remote lock*. NOTE: DO NOT SCREW THE REMOTE LOCKS IN YET.





Remove Plug in Centrelock

4

5

Remove Ø5mm plug in the drive tab on the rear of the centrelock and discard.





Pull the *free-ends* of the *rods* out through the *centrelock cutout*.

Insert the **rod free-ends** into the two **Ø5 drive holes** on the rear of the centrelock.

Insert the centrelock into the *centrelock cutout* and secure with two *#8x13mm lock body screws.*



PLEASE TURN PAGE FOR STEPS 6 - 10



www.ausloc.com

Austral Lock

South Melbourne

PO Box 52